

B&W Communication Problem

Model 6310 PA/VA - Ver 2.8A1
Hardware Version 8 , Firmware 7(10)

```
===== RANGELY =====  
RANGELY - 401 - TLA 6  
  
1 - Data collection menu  
2 - Setup database  
3 - Plot historical data  
4 - View manual/temp, notes, fft  
5 - performance Reports  
6 - Autoprint plots/reports  
7 - Utilities  
8 - select different Machine  
  
Battery 11.2 V      May 23 05:16:42 2007
```

With keyboard attached, hit Ctrl+Alt+Del, when screen flashes, press and hold F10 key

B&W Communication Problem

```
CARD-586  SETUP                                     (C)Copyright SEIKO EPSON Corp. 1997
Main menu
Device
  [FDD]
  [HDD]
  [Video]
  [Serial port]
  [Parallel port]
  [Real time clock]
  [Keyboard]
  [Memory]
  [Password]
  [User accessible CMOS area]

Minimizer
  [Power management control]
  [Power save timer]
  [Event configuration]

Information
  [BIOS information]

Press Enter key to [Set and exit  ] at this choice

Tab/↑/↓:Move cursor, Enter:Select, Esc:Cancel and terminate
```

Arrow down, hit enter on the parallel port menu

B&W Communication Problem

```
CARD-586  SETUP                                     (C)Copyright SEIKO EPSON Corp. 1997
Parallel port
External parallel port status

Primary parallel port (378h) is not found
Secondary parallel port (278h) is not found

Internal parallel port =[Primary      ]
                        mode =◀Bi-directional ▶

Press Enter key to [Set and exit  ] at this choice

Tab/↑/↓:Move cursor, ←/→:Change choice, Esc:Cancel, F1:Help
```

Make sure internal parallel port is in **bi-directional** mode, then select Set and Exit at this window and the next window to reboot